



Kemo Electronic GmbH


Mato Vukovic
 Leher Landstr. 20
 27607 Geestland
 Germany

Phone: +49 4743 9338-0
 Fax: +49 4743 9338-22


http://www.kemo-electronic.de
 email: info@kemo-electronic.de

HR.Nr. HRB 111 486
 UstNr: DE 814 380 369

M040N - Universal preamplifier



M040N



For microphones and diverse usages. This mini module is simply connected between a power amplifier (e.g. M032N | Amplifier 12 W, universal) and a weak signal source (e.g. microphones).


Available accessory:

- M031N - Amplifier 3,5 W, universal
- M032N - Amplifier 12 W, universal
- M032S - Universal Amplifier 12 W "Plug & Play"
- M033N - Amplifier 18 W, universal
- M034 - Amplifier 40 W, universal
- M034N - Power Amplifier 40 W
- M055 - Stereo amplifier 3 W

Technical Data:

- Operating voltage: approx. 9 - 24 V/DC
- Frequency range: approx. 20 - 20.000 Hz ± 3 dB
- Input voltage: approx. 2 - 50 mV
- Output voltage: approx. 0,2 - 5 V
- Input impedance: approx. 50 k Ω
- Output impedance: approx. <1 k Ω
- Amplification: approx. 40 dB (100 x) $\pm 10\%$
- Distortion: <0,02%
- Current consumption: <5 mA
- Dimensions: approx. 30 x 25 x 15 mm (without fastening straps)

Anschluss für dynamische Mikrofone und andere Signalquellen



Anschluss für Elektretmikrofone

