



**Kemo Electronic GmbH**

Mato Vukovic  
 Leher Landstr. 20  
 27607 Geestland  
 Germany

Phone: +49 4743 9338-0  
 Fax: +49 4743 9338-22

<http://www.kemo-electronic.de>  
 email: [info@kemo-electronic.de](mailto:info@kemo-electronic.de)

HR.Nr. HRB 111 486  
 UstNr: DE 814 380 369

## M032S - Universal Amplifier 12 W "Plug & Play"



Amplifying module with jacks used for the signal input and for the power supply. Inserted loudspeaker regulator and loudspeaker connection are over the cables. Available accessory: M040N - Universal preamplifier

### Technical Data:

Operating voltage: 6 - 16 V/DC  
 Current consumption: max. 800 mA  
 Input sensitivity: <80 mV  
 Loudspeaker connection: 4 - 16 Ohm  
 Music power: max. 12 W with 16 V/DC at a 4 Ohm Loudspeaker  
 Frequency response: approx. 40 - 20.000 Hz  
 Power supply jack: for mains plug 2,1 mm  
 Dimensions: approx. 73 x 60 x 43 mm (without fastening straps)



M032S

