


**Kemo Electronic GmbH**

Mato Vukovic
 Leher Landstr. 20
 27607 Geestland
 Germany

Phone: +49 4743 9338-0
 Fax: +49 4743 9338-22

<http://www.kemo-electronic.de>
 email: info@kemo-electronic.de

HR.Nr. HRB 111 486
 UstNr: DE 814 380 369

M128N - HF Detector (Mini Spy Finder)**M128N**

By means of this searching device bugging devices which are active in the room, computer or telephone can be located. Thus it is possible to find hidden bugging devices (bugs, mini spys).

The device responds to bugging devices with transmitting frequencies of approx. 30 MHz - 3.6 GHz with transmitter powers usual for bugs.

Display: 1 x LED for the turn-on control, 1 LED for indication of receipt from one transmitter (the closer you get to the transmitter, the faster this LED flashes). A 9 V/DC block battery is necessary for operation.

Technical Data:

Operating voltage: 9 V/DC block battery

Current consumption: < 15 mA

Frequency range: approx. 30 MHz - 3.6 GHz

Display: LED

Dimensions: approx. 102 x 61 x 26 mm

