

**Kemo Electronic GmbH**

Mato Vukovic  
 Leher Landstr. 20  
 27607 Geestland  
 Germany

Phone: +49 4743 9338-0  
 Fax: +49 4743 9338-22

<http://www.kemo-electronic.de>  
 email: [info@kemo-electronic.de](mailto:info@kemo-electronic.de)

HR.Nr: HRB 111 486  
 UstNr: DE 814 380 369

## M149N - Solar Charging Controller 12 V/DC, 10 A / 20 A



This solar charging controller is connected between a solar cell 12 V/DC (open circuit voltage 14 - 30 V/DC) and a battery 12 V/DC to prevent an overcharge of the battery. LED displays for "battery full" (approx. 14.4 V/ DC) and "charging".

### **Technical Data:**

Input voltage solar cell panels: 14 - 30 V/DC open circuit voltage  
 Nominal voltage: 12 V/DC  
 Max. input current: 10 A, short-time till 5 min: 20 A  
 Inrush voltage: battery voltage approx. <13.4 V  
 Interrupting voltage: battery voltage approx. >14.4 V  
 Displays: 1 LED for "CHARGING", 1 LED for "BATTERY FULL"  
 Own power consumption: <2.5 mA (LED switched on)  
 Dimensions: approx. 72 x 50 x 42 mm (without fastening straps)